RED FANG

red' fang' n. a 12" guitar speaker with unique British voicing, a large alnico magnet, smooth distortion, and rich harmonics

Impedance
Power Rating**
Voice Coil Diameter
Coil Material
Flat/Round Coil Wire
Coil Former Material
Basket Type
Cone Surround Material
Dust Cap Material
Magnet Weight
Usable Bandwidth (Fs to -3dB)
SPL*

8 ohms
30Wrms/60W peak**
1.75", 44.5mm
Copper
Round
Nomex
Stamped
Paper
Zurette
35oz. ALNICO
70Hz - 5.5kHz
103dB*



Mounting Information

Nominal Basket Diameter Baffle Hole Diameter Mounting Holes Diameter Mounting Holes B.C.D. Depth Shipping Weight 12.02", 305.2mm 10.97", 278.6mm 0.25", 6.4mm 11.63", 295.3mm 6.2", 157.5mm 11 lbs., 5 kg.

Application Notes

Thiele-Small Parameters

Impedance (Re)
Coil Inductance (Le)
Total Q (Qts)
Efficiency Bandwidth Product (EBP)
Voice Coil Overhang (Xmax)
Surface Area of Cone (Sd)

5.72 ohms 0.39mH 0.70 131 0.47mm 519.5cm² "Vintage British sound with warm undertones and high-end sparkle."

- * Published sensitivity is an average of multiple points representing the measured output of the device (1W-1m) across the usable frequency range from 200Hz-5kHz.
- ** EIA 426A noise source and test standard. Eminence voice coil technology often results in guitar speakers that dramatically exceed the power rating of other manufacturer's products. Such ratings are not meant to imply the Eminence woofers are not equally suitable for lower-power "Class A" valve amplifiers as they are for high gain valve and transistor amplification.

P. O. Box 360 Eminence, KY 40019 USA 502.845.5622 phone 502.845.5653 fax info@eminence.com www.eminence.com

Eminence Speaker

FORM 96254

